

Digital Resistance Meter OD-3



The ohmmeter OD-3 is a portable instrument designed for the measuring of electrical resistances of firing circuits.

The equipment has an automatic power-on system when the firing line is connected to the terminals.

The device has a 8x2 LCD screen for resistance and battery status indication.

This resistance meter has been designed according to the EN-13763-26 Norm.

Technical Data

Measuring range	0 - 2000 Ω	
Accuracy	0 Ω - 4 Ω:	≤ 0,2 Ω
	4 Ω - 1000 Ω:	< 5 % or 10 Ω (whichever is lower)
	> 1000 Ω:	< 20 Ω
Resolution:	0 Ω - 1000 Ω:	0.1 Ω
	> 1000 Ω:	1 Ω
Measuring current	7 mA (Typ.)	
Power supply	3 x AAA alkaline battery	
Weight	270 gr	
Dimensions	155 x 45 x 75 mm	

The equipment is supplied with protective and carrying pouch.

Not valid for use in gassy mines.

Refer to the instruction manual for safety and operating mode.

The documentation described herein shall not be considered as contractual commitment.

VIBRAQUIPO

C/ Gaiteiro de Soutelo, 3 Bajo
 36004 Pontevedra (Spain)
 Phone: (+34) 986 86 02 72
 vibraquipo@vibraquipo.com
 www.vibraquipo.com